


Multifunction timer module RUW 101MW
Programming
Timing range selection

Function selection Timing range selection



0.1...1 s



0.1...10 s



0.1...1 min



1...10 min



0.1...1 h



1...10 h



0.1...1 day



1...10 days

Function selection

Selection	Function	Control	Function diagram	Control scheme
	On-delay timer E	Series control		
	Monostable with maintained control Wu	Series control		
	Flashing relay, starting On-delay phase Bi	Series control		
	Flashing relay, starting Off-delay phase Bp	Series control		
	Off-delay timer R	Control by external contact (S)		
	Monostable with pulse control Ws	Control by external contact (S)		
	Monostable, starting on de-energisation Wa	Control by external contact (S)		
	On-delay timer Es	Control by external contact (S)		

Power off

Contact open

U: voltage

S: external control

Power on

Contact closed

R: relay RUM ●●●

t: adjustable time delay